

DESCRIPTION

The PT2479L is a monolith integrated motor driver designed for printers, scanners or home appliance. The built-in two channel H-bridges designs for driving a bipolar stepping motor or two DC-brushed motors.

The H-bridge driver is consists by all of N-channel MOSFET allows driving up to 2.5A maximum output current ($V_M=24\text{ V}$, $T_a=25^\circ\text{C}$).

The dual-input interface is a common configuration for the motor driver; it is very versatile to control the H-bridge switches to determinate motor winding current and phase. The motor current decay mode is programmable by a tri-states input pin.

The PT2479L is available in a 28-pin HTSSOP package with thermal pad.


APPLICATIONS

- Automatic teller machines
- Video security cameras
- Printers
- Scanners
- Office automation machines
- Amusement machines
- Factory automation
- Robotics



FEATURES

- 8V to 40V maximum supply voltage
- 2.5A maximum driving current at $V_M=24\text{V}$ (with additional heatsink)
- Low switches conduction resistance: $0.4\Omega(\text{typ})$, high side + low side in $T_j=25^\circ\text{C}$.
- Dual-in control interface
- H-bridge driver outputs with four levels PWM constant current regulation.
- Winding current decay modes
 - mixed decay
 - slow decay
 - fast decay
- Drives single bipolar stepping motor or dual brushed dc motors
- Built-in 3.3V reference voltage output
- Low-power sleep mode
- Protection features
 - Over current protection (OCP)
 - Thermal shutdown (TSD)
 - VM under voltage lock out (UVLO)
 - Fault indication output (FALTN)

BLOCK DIAGRAM



APPLICATION CIRCUIT




ORDER INFORMATION

Valid Part Number	Package Type	Top Code
PT2479L-HT	28 Pins, HTSSOP	PT2479L-HT

PIN CONFIGURATION

Top View



PIN DESCRIPTION

Pin Name	I/O	Description	Pin No.
CP1	I	External flying capacitor for charge pump, Connect a 0.01 μ F/50V low-ESR ceramic capacitor between CP1 and CP2.	1
CP2	I		2
VCP	O	High-side gate drive supply voltage (Connect a 0.1 μ F/50V ceramic capacitor and a 1M Ω resistor to VM.)	3
VMA	-	H-Bridge A power supply	4
OUT1A	O	H-Bridge A output 1	5
ISENA	I	H-Bridge A current sense / GND	6
OUT2A	O	H-Bridge A output 2	7
OUT2B	O	H-Bridge B output 2	8
ISENB	I	H-Bridge B current sense / GND	9
OUT1B	O	H-Bridge B output 1	10
VMB	-	H-Bridge B power supply	11
VREFA	I	H-Bridge A current set reference input	12
VREFB	I	H-Bridge B current set reference input	13
GND	-	Device ground	14
3V3REF	O	3.3V reference voltage output	15
RSTN	I	Reset input (L=Initialize all of internal logic registers and disables H-bridge outputs)	16
SLEPN	I	Sleep mode input (H=device enable, L=low-power sleep mode)	17
FALTN	O	Fault, Logic low when fault condition appear (OCP, OTP)	18
DECAY	I	Decay mode (Low = slow decay, open = mixed decay, high = fast decay)	19
IN2A	I	H-Bridge A Control Input 2	20
IN1A	I	H-Bridge A Control Input 1	21
IN1B	I	H-Bridge B Control Input 1	22
IN2B	I	H-Bridge B Control Input 2	23
I0A	I	H-Bridge A current set (Sets H-bridge A current: 00 = 100%, 01 = 71%, 10 = 38%, 11 = 0%)	24
I1A	I		25
I0B	I	H-Bridge B current set (Sets H-bridge B current: 00 = 100%, 01 = 71%, 10 = 38%, 11 = 0%)	26
I1B	I		27
GND	-	Device ground	28
Thermal Pad	-	Enhance the package heat dissipation, must connecting to the GND plane through the thermal via.	-



IMPORTANT NOTICE

Princeton Technology Corporation (PTC) reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and to discontinue any product without notice at any time.

PTC cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a PTC product. No circuit patent licenses are implied.

Princeton Technology Corp.
2F, 233-1, Baociao Road,
Sindian Dist., New Taipei City 23145, Taiwan
Tel : 886-2-66296288
Fax: 886-2-29174598
<http://www.princeton.com.tw>